




Systemleuchten für Zentralversorgung

Abstandstabelle ebene Fluchtwege / Tabellenangaben in Meter

Leuchtmittel: 1,5W LED-Leiste


Lampenlichtstrom Not (DC)/Netz: 190lm / 190lm



h	2,50	3,00	3,50	4,00	4,50	5,00	5,50	6,00	6,50	7,00
a	7,80	8,50	8,70	8,70	9,00	8,80	8,20	7,40	6,90	6,70
b	3,10	3,10	3,20	2,90	2,30	2,30	2,20	1,60	1,60	1,00
c	8,10	8,60	8,90	9,20	9,10	9,00	8,60	8,60	8,20	7,80
d	3,10	3,30	3,00	3,10	3,00	2,70	2,20	1,60	1,60	0,60

Leuchtmittel: 3W LED-Leiste


Lampenlichtstrom Not (DC)/Netz: 350lm / 350lm



h	2,50	3,00	3,50	4,00	4,50	5,00	5,50	6,00	6,50	7,00	7,50	8,00	8,50	9,00	9,50	10,00
a	9,50	10,00	10,70	11,50	11,80	12,00	12,20	12,40	12,40	11,90	11,40	9,90	9,50	9,30	9,00	8,10
b	3,80	4,10	4,20	4,30	4,30	4,30	4,10	3,30	3,20	3,30	3,20	2,40	1,70	1,70	1,20	1,00
c	10,00	10,70	11,40	11,90	12,40	12,60	12,80	12,40	12,30	11,30	11,60	11,80	11,40	11,00	10,60	7,80
d	4,00	4,30	4,40	4,50	4,70	4,00	4,10	4,20	4,10	3,50	3,10	2,60	1,60	1,60	1,20	0,50

Leuchtmittel: 6W LED-Leiste


Lampenlichtstrom Not (DC)/Netz: 600lm / 600lm



h	2,00	3,00	4,00	5,00	6,00	7,00	8,00	9,00	10,00	11,00	12,00
a	10,40	12,30	13,40	15,10	16,00	16,50	16,80	15,90	15,10	12,70	12,00
b	4,30	4,90	5,70	5,80	5,90	5,50	4,30	4,30	3,50	2,40	2,20
c	10,70	12,90	14,40	15,50	16,50	17,00	16,80	15,30	15,70	15,20	14,50
d	4,40	5,20	5,70	6,00	6,20	5,50	5,60	4,80	3,90	2,20	2,20

Leuchtmittel: 10W LED-Leiste

Lampenlichtstrom Not (DC)/Netz: 1.050lm / 1.050lm




h	2,00	3,00	4,00	5,00	6,00	7,00	8,00	9,00	10,00	11,00	12,00	13,00	14,00	15,00	16,00	17,00
a	11,10	13,90	16,10	17,00	18,70	19,90	20,30	21,10	21,50	21,50	20,30	19,10	16,30	15,40	15,70	13,90
b	4,50	5,60	6,40	7,20	7,30	7,60	7,60	7,10	5,70	5,50	5,70	4,40	3,30	1,50	1,20	1,00
c	11,50	14,80	16,90	18,30	19,50	20,60	21,40	21,80	21,50	21,10	19,70	20,20	19,50	18,80	17,90	13,60
d	4,60	6,10	6,70	7,30	7,60	7,80	6,90	7,10	7,20	6,90	5,60	4,80	2,90	1,40	1,20	1,00

Einzelbatterieleuchten

Abstandstabelle ebene Fluchtwege / Tabellenangaben in Meter

Leuchtmittel: 1,5W LED-Leiste


Lampenlichtstrom Not/Netz: 190lm/190lm – Nennbetriebsdauer: 1h/3h



h	2,50	3,00	3,50	4,00	4,50	5,00	5,50	6,00	6,50	7,00
a	7,80	8,50	8,70	8,70	9,00	8,80	8,20	7,40	6,90	6,70
b	3,10	3,10	3,20	2,90	2,30	2,30	2,20	1,60	1,60	1,00
c	8,10	8,60	8,90	9,20	9,10	9,00	8,60	8,60	8,20	7,80
d	3,10	3,30	3,00	3,10	3,00	2,70	2,20	1,60	1,60	0,60

Leuchtmittel: 1,5W LED-Leiste


Lampenlichtstrom Not/Netz: 190lm/190lm – Nennbetriebsdauer: 8h



h	2,50	3,00	3,50	4,00	4,50	5,00	5,50	6,00	6,50	7,00
a	7,80	8,50	8,70	8,70	9,00	8,80	8,20	7,40	6,90	6,70
b	3,10	3,10	3,20	2,90	2,30	2,30	2,20	1,60	1,60	1,00
c	8,10	8,60	8,90	9,20	9,10	9,00	8,60	8,60	8,20	7,80
d	3,10	3,30	3,00	3,10	3,00	2,70	2,20	1,60	1,60	0,60

Leuchtmittel: 3W LED-Leiste

Lampenlichtstrom Not/Netz: 350lm/350lm – Nennbetriebsdauer: 1h/3h



h	2,50	3,00	3,50	4,00	4,50	5,00	5,50	6,00	6,50	7,00	7,50	8,00	8,50	9,00	9,50	10,00
a	9,50	10,00	10,70	11,50	11,80	12,00	12,20	12,40	12,40	11,90	11,40	9,90	9,50	9,30	9,00	8,10
b	3,80	4,10	4,20	4,30	4,30	4,30	4,10	3,30	3,20	3,30	3,20	2,40	1,70	1,70	1,20	1,00
c	10,00	10,70	11,40	11,90	12,40	12,60	12,80	12,40	12,30	11,30	11,60	11,80	11,40	11,00	10,60	7,80
d	4,00	4,30	4,40	4,50	4,70	4,00	4,10	4,20	4,10	3,50	3,10	2,60	1,60	1,60	1,20	0,50